



# ENERBOX 6 - 7 - 8 - 10 - 13 - 15

- Caricabatteria semplice ed affidabile per uso hobbistico.
- Chargeur de batterie simple et fiable, pour bricoleurs.
- Battery charger, simple and reliable, for hobbyist users.
- Cargador de bateria, simple y fiable, para uso no profesional.
- Batterieladegerät, einfach und zuverlässig, für Hobby-Anwender.
- Простое в эксплуатации и надежное зарядное устройство для автолюбителей.



Ah	ENERBOX 6	ENERBOX 7	ENERBOX 8	ENERBOX 10	ENERBOX 13	ENERBOX 15
	10-40 Ah	15-80 Ah	10-50 Ah(6V) 15-80 Ah(12V)	15-60 Ah(6V) 30-100 Ah(12V)	30-100 Ah	30-120 Ah(12V) 15-80 Ah(24V)

**24V**  
ENERBOX 15

**12V**  
ENERBOX 6-7-8-10-13-15

**6V**  
ENERBOX 8-10



## Technical specifications

	CODE	Input voltage	Absorbed power	Battery Voltage	Effective Current	EN60335	Box volume	Box weight	Box size (mm)	PCS per masterbox	PCS per Euro pallet	Bar code
ENERBOX 6	71050	230V~1ph	75W	12V	5A	4A	0,006m <sup>3</sup>	2,7	260x140x180	6	216	8004386710500
ENERBOX 7	71080	230V~1ph	95W	12V	6,1A	4,9A	0,010m <sup>3</sup>	4	260x260x155	4	144	8004386710807
ENERBOX 8	71100	230V~1ph	110W 70W	12V 6V	7A	5,6A	0,010m <sup>3</sup>	4,1	260x260x155	4	144	8004386711002
ENERBOX 10	71150	230V~1ph	110W 80W	12V 6V	7A	6A	0,010m <sup>3</sup>	4,4	260x260x155	4	144	8004386711507
ENERBOX 13	71166	230V~1ph	160W	12V	11,5A	9,2A	0,010m <sup>3</sup>	4,6	260x260x155	4	144	8004386711668
ENERBOX 15	71200	230V~1ph	170W 180W	24V 12V	12,2A	5,3A 9,8A	0,010m <sup>3</sup>	4,6	260x260x155	4	144	8004386712009